

Serial No.: 10/532,090
Atty. Docket No.: P70540US0

IN THE CLAIMS:

Please amend the claims as follows:

Claims 1-13. (canceled).

14. (Currently Amended) ~~System~~ A system for spatial analysis of a physical quantity whose spatial values (S1 to Sn) are respectively represented by measurement pulses (I1 to In) whose order in time is representative of those values, ~~this said~~ system comprising a plurality of processing units (U1 to Un; p_n) for processing said measurement pulses, said processing units being arranged in one or more rows and each having an output (SOR1 to SORn) at which, during successive processing cycles, a measurement pulse that is processed therein ~~is may be~~ delivered to form ~~the an~~ output signal (SU) of said system, wherein each of said processing units (U1 to Un; p_n) further includes an inhibition unit ~~means~~ (BI) for inhibiting, in other units of said one or more rows ~~row~~ and during a processing cycle, ~~the~~ passage toward the outputs (SOR1 to SORn) of those other units of respective measurement pulses that are processed therein, and thereby preventing said respective measurement pulses ~~them~~ from forming said output signal (SU) of the system, if those measurement pulses are ordered later in the

Serial No.: 10/532,090
Atty. Docket No.: P70540US0

processing cycle concerned than the pulse processed in the unit concerned.

15. (Currently Amended) The system ~~System~~ according to claim 14, further comprising a counter ~~means~~ (N) for counting the measurement pulses delivered at the output (SU) of said system over a plurality of successive processing cycles and for interrupting (INT1 to INTn) the processing of said measurement pulses if the number of pulses delivered in this way reaches a predetermined value.

16. (Currently Amended) The system ~~System~~ according to claim 14, wherein said spatial values (S1 to Sn) representing said physical quantity are instantaneous amplitudes thereof measured locally during respective successive processing cycles, and each of said units (U1 to Un; p_n) further includes a converter ~~comprises conversion means~~ (C1 to Cn) for converting said amplitudes into measurement pulses (I1 to In) ordered in time.

17. (Currently Amended) The system ~~System~~ according to claim 16, wherein said converter includes a control element that brings ~~conversion means include control means that bring about the passage~~

Serial No.: 10/532,090
Atty. Docket No.: P70540US0

to the output of said measurement pulse in the processing unit of said row in which the order in time of that measurement pulse is the earliest in said cycle concerned and therefore represents the maximum value of the values of the physical quantity detected by the respective processing units (p_n) during a processing cycle.

18. (Currently Amended) The system ~~System~~ according to claim 16, wherein said converter includes a control element that brings ~~conversion means include control means that bring about the passage~~ to the output of said measurement pulse in the processing unit in said row in which that pulse is the latest in said cycle concerned and therefore represents the minimum value of all the values of the physical quantity detected by the respective processing units (p_n) during a processing cycle.

19. (Currently Amended) The system ~~System~~ according to claim 17, wherein said control element includes ~~means include~~ a comparator to which is applied, on the one hand, the amplitude appearing in the processing unit (U_1 to U_n ; p_n) concerned during a processing cycle and, on the other hand, a generator of a reference signal variable in accordance with a profile repeated during each processing cycle; said comparator being adapted to supply an

Serial No.: 10/532,090
Atty. Docket No.: P70540US0

inhibition signal to said adjacent units if said reference signal becomes equal to said amplitude during a processing cycle.

20. (Currently Amended) The system ~~System~~ according to claim 19, wherein said reference signal generator is adapted to generate a monotonously increasing reference signal and said measurement pulse corresponds to the lowest spatial value of said physical quantity during a processing cycle.

21. (Currently Amended) The system ~~System~~ according to claim 18, wherein said control element includes ~~means include~~ a comparator to which is applied, on the one hand, the amplitude appearing in the processing unit (U_1 to U_n ; p_n) concerned during a processing cycle and, on the other hand, a generator of a reference signal variable in accordance with a profile repeated during each processing cycle; said comparator being adapted to supply an inhibition signal to said adjacent units if said reference signal becomes equal to said amplitude during a processing cycle and wherein said reference signal generator reference signal is adapted to generate a monotonously decreasing reference signal and said measurement pulse corresponds to the highest spatial value of said physical quantity during a processing cycle.

Serial No.: 10/532,090
Atty. Docket No.: P70540US0

22. (Currently Amended) The system ~~System~~ according to claim 14, wherein said system ~~it~~ includes a plurality of rows of processing units (p_n) forming a matrix, said units being arranged in rows and in columns, and each processing unit further comprises a selector ~~selection means~~ for bringing about the selective inhibition of the passage toward the output of respective measurement pulses in the units adjacent the processing unit concerned, oriented in the direction of a column, a row or a diagonal of said matrix.

23. (Currently Amended) The system ~~System~~ according to claim 22, wherein each of said processing units (p_n) ~~comprises~~ includes a turning filter circuit to which said amplitude is applied to form a vectorial signal whose norm is represented by the order of said measurement pulse and whose phase represents the orientation of the spatial variation of said physical quantity, said ~~selection means~~ selector further comprising a comparator ~~means~~ for comparing the phase of said vectorial signal to the order in time of said pulse and for authorizing, as a function of the phase position of said measurement pulse, the inhibition of the processing units selectively situated in a column, a row or a diagonal of said matrix.

Serial No.: 10/532,090
Atty. Docket No.: P70540US0

24. (Currently Amended) The system ~~System~~ according to claim 23, wherein said selector ~~selection means~~ further includes a multiplexer ~~comprise means~~ for selectively authorizing the passage to said output of the processing unit concerned of the measurement pulse that is processed therein or of the phase information of that pulse.

25. (Currently Amended) The system ~~System~~ according to claim 14, wherein each processing unit is connected to an element responsive to said physical quantity and supplying an analog signal representative of the local evolution thereof and forming said amplitudes during said successive processing cycles.

26. (Currently Amended) The system ~~System~~ according to claim 25, wherein said physical quantity is the luminance emanating from a scene observed by said system and said sensitive element is a photosensor forming part of each of said processing units.